



## **Avaya Solution & Interoperability Test Lab**

---

# **Application Notes for configuring Enghouse Interactive Communications Portal 9.0 with Avaya Aura® Session Manager R6.3 and Avaya Aura® Communication Manager R6.3 - Issue 1.0**

## **Abstract**

These Application Notes describe the configuration steps for Enghouse Interactive Communications Portal 9.0 to successfully interoperate with Avaya Aura® Session Manager R6.3 and Avaya Aura® Communication Manager R6.3. Communications Portal is an IVR application that connects to Session Manager as a SIP Entity.

Readers should pay attention to section 2, in particular the scope of testing as outlined in Section 2.1 as well as the observations noted in Section 2.2, to ensure that their own use cases are adequately covered by this scope and results.

Information in these Application Notes has been obtained through DevConnect compliance testing and additional technical discussions. Testing was conducted via the DevConnect Program at the Avaya Solution and Interoperability Test Lab.

# 1. Introduction

These Application Notes describe the configuration steps for Enghouse Interactive Communications Portal 9.0 to successfully interoperate with Avaya Aura® Session Manager R6.3 and Avaya Aura® Communication Manager R6.3.

Enghouse Interactive Communications Portal (formerly Syntellect Communications Portal) is an open, standards-based platform with integrated application development and management components.

- Voice self-service solutions, such as interactive voice response (IVR), interactive voice and video response (IVVR), outbound dialing, and speech-enabled self-service systems.
- SMS, email, standards-based voice mail.
- Contact center solutions, including outbound dialing, intelligent routing applications and screen pop applications.
- Unified communications solutions, including standards-based voice-mail systems and applications that combine traditional voice, IP telephony, video messaging, SMS, email, and fax communication.

## 2. General Test Approach and Test Results

The IVR application telephony functionality of Communications Portal 9.0 (CP) was the only one tested. This IVR application (CP script) connects to Session Manager as a SIP Trunk entity and can be integrated with Communication Manager by passing SIP calls to and from the PBX. Session Manager directs the call over SIP trunks to CP scripts which in turn handles the call depending on the digits dialed using SIP signaling. Communications Portal utilizes Dialogic HMP 3.0 driver to perform all telephony functions on the server. This Dialogic Host Media Processing (HMP) software 3.0 facilitates the Communications Portal connectivity to Session Manager.

DevConnect Compliance Testing is conducted jointly by Avaya and DevConnect members. The jointly-defined test plan focuses on exercising APIs and/or standards-based interfaces pertinent to the interoperability of the tested products and their functionalities. DevConnect Compliance Testing is not intended to substitute full product performance or feature testing performed by DevConnect members, nor is it to be construed as an endorsement by Avaya of the suitability or completeness of a DevConnect member's solution.

## 2.1. Interoperability Compliance Testing

The interoperability compliance test included both feature functionality and serviceability testing. The feature functionality testing focused on placing various calls to the Communications Portal IVR:

- **Basic Inbound/Outbound** – Tests inbound calls to Enghouse Interactive Communications Portal.
- **Call Hold** – Tests held calls to/from Enghouse Interactive Communications Portal.
- **Call Transfer** – Tests transferred calls to/from Enghouse Interactive Communications Portal.
- **IVR Functionality** – Tests of various IVR features like is ANI/DNIS detection, leaving voice message/voice mail (Recording), DTMF collection, Barge-in and Trombone Referral on the Enghouse Interactive Communications Portal.
- **Failover/Service** – Tests the behaviour of Enghouse Interactive Communications Portal when there are certain failed conditions.

The serviceability testing focused on verifying the ability of Communications Portal to recover from disconnection and reconnection to the Avaya solution.

## 2.2. Test Results

All functionality and serviceability test cases were completed successfully, however the following was observed only when shuffling was on (**Direct IP to IP Audio Connections** set to **Y**).

- From a H.323 or SIP IP desk phone on Communication Manager calling to the Communications Portal IVR system playing an announcement via SIP trunk (Session Manager), then pressing Hold/Resume in quick succession leads to the loss of RTP. This is due to the reINVITE being sent by Communication Manager before the ACK is received by Communications Portal and a “491 request pending” is received. This may be causing this issue, simply due to a delay and the reINVITE/ACK sequence going out of sync. Note that is not an issue if Hold/Resume is used in a “normal” fashion or when shuffling is off (**Direct IP to IP Audio Connections** set to **N**).

## 2.3. Support

Technical support can be obtained for Enghouse Interactive as follows:

### USA


- Email: [scpsupport@enghouse.com](mailto:scpsupport@enghouse.com)
- Website: <http://enghouseinteractive.com/support.php>
- Phone: +1 800.788.9730 Self-Service
- Phone: +1 800.872.2272 Live-Service

### EMEA

- Email: [supportenvox@syntellect.com](mailto:supportenvox@syntellect.com)
- Website: [http://enghouseinteractive.co.uk/support/contact\\_support/](http://enghouseinteractive.co.uk/support/contact_support/)
- Phone: +44 203 357 3001

### 3. Reference Configuration

The configuration in **Figure 1** will be used to compliance test Enghouse Interactive Communications Portal 9.0 with Session Manager and Communication Manager using SIP signalling over SIP trunks to route calls from Communication Manager to Communications Portal 9.0.



**Figure 1: Connection of Enghouse Interactive Communications Portal 9.0 with Avaya Aura® Session Manager R6.3 and Avaya Aura® Communication Manager R6.3**

## 4. Equipment and Software Validated

The following equipment and software were used for the sample configuration provided:

Equipment/Software	Release/Version
Avaya Aura <sup>®</sup> System Manager running on a Virtual Platform	R6.3 SP7 Build 6.3.0.8.5682-6.3.8.3204 Software Update Revision 6.3.7.7.2275
Avaya Aura <sup>®</sup> Session Manager running on a Virtual Platform	R6.3 SP5 6.3.5.0.635005
Avaya Aura <sup>®</sup> Communication Manager running on a Virtual Platform	R6.3 SP6 R016x.03.0.124.0
Avaya G430 Gateway	33.12.0 /1
Avaya 9620 H323 Deskphone Avaya 9608 H323 Deskphone	H.323 Release s3.186a H.323 Release 6.2009
Avaya 9641 SIP Deskphone Avaya 9630 SIP Deskphone	SIP Release 6.2.1.26 SIP Release 2.6.8.4
Enghouse Interactive Communications Portal running on Windows 2012 Server Dialogic HMP Driver	Communications Portal 9.0 PRC2 Dialogic HMP 3.0 SU349

## 5. Configure Avaya Aura® Communication Manager

The configuration and verification operations illustrated in this section were all performed using Communication Manager System Administration Terminal (SAT). The information provided in this section describes the configuration of Communication Manager for this solution. For all other provisioning information such as initial installation and configuration, please refer to the product documentation in **Section 10**.

The configuration operations described in this section can be summarized as follows:

- Verify System Parameters Customer Options.
- System Features and Access Codes.
- Administer Dial Plan.
- Administer Route Selection for Communications Portal calls.
- Configure SIP Trunk.

**Note:** The configuration of PSTN trunks and routes are outside the scope of these Application Notes.

### 5.1. Verify System Parameters Customer Options

The license file installed on the system controls these attributes. If a required feature is not enabled or there is insufficient capacity, contact an authorized Avaya sales representative. Use the **display system-parameters customer-options** command to determine these values. On **Page 2**, verify that **Maximum Administered SIP Trunks** has sufficient capacity. Each call that receives IVR treatment from Communications Portal uses a minimum of one SIP trunk. Calls that are routed back to stations commissioned on Communication Manager, or calls that are routed back to Communication Manager to access the PSTN, use 2 SIP trunks.

display system-parameters customer-options		Page	2 of 11
OPTIONAL FEATURES			
IP PORT CAPACITIES		USED	
Maximum Administered H.323 Trunks:		12000	250
Maximum Concurrently Registered IP Stations:		18000	2
Maximum Administered Remote Office Trunks:		12000	0
Maximum Concurrently Registered Remote Office Stations:		18000	0
Maximum Concurrently Registered IP eCons:		414	0
Max Concur Registered Unauthenticated H.323 Stations:		100	0
Maximum Video Capable Stations:		18000	0
Maximum Video Capable IP Softphones:		18000	0
<b>Maximum Administered SIP Trunks:</b>		<b>24000</b>	<b>319</b>
Maximum Administered Ad-hoc Video Conferencing Ports:		24000	0

On **Page 3**, ensure that both **ARS** and **ARS/AAR Partitioning** are set to **y**.

display system-parameters customer-options		Page	3 of 11
OPTIONAL FEATURES			
Abbreviated Dialing Enhanced List?	y	Audible Message Waiting?	y
Access Security Gateway (ASG)?	n	Authorization Codes?	y
Analog Trunk Incoming Call ID?	y	CAS Branch?	n
A/D Grp/Sys List Dialing Start at 01?	y	CAS Main?	n
Answer Supervision by Call Classifier?	y	Change COR by FAC?	n
	<b>ARS? y</b>	Computer Telephony Adjunct Links?	y
	<b>ARS/AAR Partitioning? y</b>	Cvg Of Calls Redirected Off-net?	y
ARS/AAR Dialing without FAC?	y	DCS (Basic)?	y

On **Page 5**, ensure that **Uniform Dialing Plan** is set to **y**.

display system-parameters customer-options		Page	5 of 11
OPTIONAL FEATURES			
Multinational Locations?	n	Station and Trunk MSP?	y
Multiple Level Precedence & Preemption?	n	Station as Virtual Extension?	y
Multiple Locations?	n	System Management Data Transfer?	n
Personal Station Access (PSA)?	y	Tenant Partitioning?	y
PNC Duplication?	n	Terminal Trans. Init. (TTI)?	y
Port Network Support?	y	Time of Day Routing?	y
Posted Messages?	y	TN2501 VAL Maximum Capacity?	y
		<b>Uniform Dialing Plan? y</b>	
Private Networking?	y	Usage Allocation Enhancements?	y



## 5.2. System Features and Access Codes

For the testing, **Trunk-to Trunk Transfer** was set to **all** on **page 1** of the **system-parameters features** page. This is a system wide setting that allows calls to be routed from one trunk to another and is usually turned off to help prevent toll fraud. An alternative to enabling this feature on a system wide basis is to control it using COR (Class of Restriction). See **Section 10** for supporting documentation.

```
display system-parameters features                                     Page 1 of 19
                                FEATURE-RELATED SYSTEM PARAMETERS
                                Self Station Display Enabled? n
                                Trunk-to-Trunk Transfer: all
                                Automatic Callback with Called Party Queuing? n
                                Automatic Callback - No Answer Timeout Interval (rings): 3
                                Call Park Timeout Interval (minutes): 10
                                Off-Premises Tone Detect Timeout Interval (seconds): 20
                                AAR/ARS Dial Tone Required? y

                                Music (or Silence) on Transferred Trunk Calls? no
                                DID/Tie/ISDN/SIP Intercept Treatment: attd
                                Internal Auto-Answer of Attd-Extended/Transferred Calls: transferred
                                Automatic Circuit Assurance (ACA) Enabled? n

                                Abbreviated Dial Programming by Assigned Lists? n
                                Auto Abbreviated/Delayed Transition Interval (rings): 2
                                Protocol for Caller ID Analog Terminals: Bellcore
                                Display Calling Number for Room to Room Caller ID Calls? n
```

Use the **display feature-access-codes** command to verify that a FAC (feature access code) has been defined for both AAR and ARS. Note that **8** is used for AAR and **9** for ARS routing.

```
display feature-access-codes                                         Page 1 of 10
                                FEATURE ACCESS CODE (FAC)
                                Abbreviated Dialing List1 Access Code:
                                Abbreviated Dialing List2 Access Code:
                                Abbreviated Dialing List3 Access Code:
                                Abbreviated Dial - Prgm Group List Access Code:
                                Announcement Access Code:
                                Answer Back Access Code:
                                Attendant Access Code:
                                Auto Alternate Routing (AAR) Access Code: 8
                                Auto Route Selection (ARS) - Access Code 1: 9      Access Code 2:
                                Automatic Callback Activation: *25      Deactivation: #25
```

### 5.3. Administer Dial Plan

It was decided for compliance testing that all calls beginning with 43 with a total length of 4 digits were to be sent across the SIP trunk to Session Manager and therefore to Communications Portal. In order to achieve this automatic alternate routing (aar) would be used to route the calls. The dial plan and aar routing analysis need to be changed to allow this.

Type **change dialplan analysis** in order to make changes to the dial plan. Ensure that **43** is added with a **Total Length** of **4** and a **Call Type** of **udp**.

change dialplan analysis						Page 1 of 12			
DIAL PLAN ANALYSIS TABLE									
Location: all						Percent Full: 2			
Dialed String	Total Length	Call Type	Dialed String	Total Length	Call Type	Dialed String	Total Length	Call Type	
2	4	ext							
3	4	ext							
43	4	udp							
5	4	ext							
6	4	ext							
7	3	dac							
8	1	fac							
9	1	fac							
*	3	fac							
#	3	fac							

### 5.4. Administer Route Selection for Communications Portal Calls

As digits **43xx** were defined in the dial plan as **udp** (Section 5.3) use the **change uniform-dialplan** command to configure the routing of the dialed digits. In the example below calls to numbers beginning with **43** that are **4** digits in length will be matched. No further digits are deleted or inserted. Calls are sent to **aar** for further processing.

change uniform-dialplan 8						Page 1 of 2		
UNIFORM DIAL PLAN TABLE								
						Percent Full: 0		
Matching			Insert			Node		
Pattern	Len	Del	Digits	Net	Conv	Num		
43	4	0		aar	n			
					n			

Use the **change aar analysis x** command to further configure the routing of the dialed digits. Calls to Communications Portal begin with **43** and are matched with the AAR entry shown below. Calls are sent to **Route Pattern 1**, which contains the outbound SIP Trunk Group.

change aar analysis 4						Page 1 of 2	
AAR DIGIT ANALYSIS TABLE							
Location: all						Percent Full: 1	
Dialed	Total		Route	Call	Node	ANI	
String	Min	Max	Pattern	Type	Num	Reqd	
43	4	4	1	unku		n	

Use the **change route-pattern *n*** command to add the SIP trunk group to the route pattern that AAR selects. In this configuration, **Route Pattern Number 1** is used to route calls to trunk group (**Grp No**) **1**, this is the SIP Trunk configured in **Section 5.5**.

change route-pattern 1													Page 1 of 3			
Pattern Number: 1 Pattern Name: SIPTRK																
SCCAN? n Secure SIP? n																
Grp	FRL	NPA	Pfx	Hop	Toll	No.	Inserted						DCS/	IXC		
No			Mrk	Lmt	List	Del	Digits						QSIG			
Dgts													Intw			
1: 1	0												n	user		
2:													n	user		
3:													n	user		
4:													n	user		
5:													n	user		
6:													n	user		
		BCC VALUE		TSC	CA-TSC		ITC BCIE		Service/Feature		PARM	No.	Numbering	LAR		
		0	1	2	M	4	W	Request				Dgts	Format			
															Subaddress	
1:	y	y	y	y	y	n	n	unre						none		
2:	y	y	y	y	y	n	n	rest						none		
3:	y	y	y	y	y	n	n	rest						none		
4:	y	y	y	y	y	n	n	rest						none		
5:	y	y	y	y	y	n	n	rest						none		
6:	y	y	y	y	y	n	n	rest						none		
6:	y	y	y	y	y	n	n	rest						none		

## 5.5. Configure SIP Trunk

In the Node Names IP form, note the IP Address of the **procr** and the Session Manager (**SM63vmpg**). The host names will be used throughout the other configuration screens of Communication Manager and Session Manager. Type **display node-names ip** to show all the necessary node names.

display node-names ip		Page 1 of 2
IP NODE NAMES		
Name	IP Address	
AES63VMPG	10.10.40.30	
PGDECT	10.10.40.50	
SM63vmpg	10.10.40.34	
default	0.0.0.0	
<b>procr</b>	10.10.40.31	
procr6	::	

In the **IP Network Region** form, the **Authoritative Domain** field is configured to match the domain name configured on Session Manager in **Section 6.2**. In this configuration, the domain name is **devconnect.local**. The **IP Network Region** form also specifies the **IP Codec Set** to be used. This codec set will be used for calls routed over the SIP trunk to Session manager as **ip-network region 1** is specified in the SIP signaling group.

display ip-network-region 1		Page 1 of 20
IP NETWORK REGION		
Region: 1		
Location: 1	<b>Authoritative Domain: devconnect.local</b>	
Name: Default region		
MEDIA PARAMETERS	Intra-region IP-IP Direct Audio: yes	
<b>Codec Set: 1</b>	Inter-region IP-IP Direct Audio: yes	
UDP Port Min: 2048	IP Audio Hairpinning? n	
UDP Port Max: 3329		
DIFFSERV/TOS PARAMETERS		
Call Control PHB Value: 46		
Audio PHB Value: 46		
Video PHB Value: 26		
802.1P/Q PARAMETERS		
Call Control 802.1p Priority: 6		
Audio 802.1p Priority: 6		
Video 802.1p Priority: 5		
H.323 IP ENDPOINTS	AUDIO RESOURCE RESERVATION PARAMETERS	
H.323 Link Bounce Recovery? y	RSVP Enabled? n	
Idle Traffic Interval (sec): 20		
Keep-Alive Interval (sec): 5		
Keep-Alive Count: 5		

In the **IP Codec Set** form, select the audio codec's supported for calls routed over the SIP trunk to Communications Portal. The form is accessed via the **change ip-codec-set n** command. Note that IP codec set 1 was specified in IP Network Region 1 shown above. Multiple codecs may be specified in the **IP Codec Set** form in order of preference; the example below includes **G.729**, **G.711MU** (mu-law) and **G.711A** (a-law), which are supported by Communications Portal.

change ip-codec-set 1

Page 1 of 2

IP Codec Set

Codec Set: 1

	Audio Codec	Silence Suppression	Frames Per Pkt	Packet Size (ms)
1:	<b>G.729</b>	<b>n</b>	<b>2</b>	<b>20</b>
2:	<b>G.711MU</b>	<b>n</b>	<b>2</b>	<b>20</b>
3:	<b>G.711A</b>	<b>n</b>	<b>2</b>	<b>20</b>
4:				
5:				

Prior to configuring a SIP trunk group for communication with Session Manager, a SIP signaling group must be configured. Configure the Signaling Group form shown below as follows:

- Set the **Group Type** field to **sip**.
- Set the **Transport Method** to the desired transport method, for compliance testing this was set to **tls**.
- The **Peer Detection Enabled** field should be set to **y** allowing the Communication Manager to automatically detect if the peer server is a Session Manager.
- Specify the node names for the procr and the Session Manager node name as the two ends of the signaling group in the **Near-end Node Name** field and the **Far-end Node Name** field, respectively. These values are taken from the **IP Node Names** form shown above.
- Set the **Near-end Node Name** to **procr**. This value is taken from the **IP Node Names** form shown above.
- Set the **Far-end Node Name** to the node name defined for the Session Manager (node name **SM63vmpg**), as per **Section 5.5**.
- Ensure that the recommended TLS port value of **5061** is configured in the **Near-end Listen Port** and the **Far-end Listen Port** fields.
- In the **Far-end Network Region** field, enter the IP Network Region configured above. This field logically establishes the **far-end** for calls using this signaling group as network region 1.
- Leave the **Far-end Domain** field blank to allow Communication Manager to accept any domain.
- The **DTMF over IP** field should remain set to the default value of **rtp-payload**. This value enables Communication Manager to send DTMF transmissions using RFC 2833.
- The **Direct IP-IP Audio Connections** field is set to **y**.
- The default values for the other fields may be used.

change signaling-group 1		Page 1 of 2	
SIGNALING GROUP			
<b>Group Number: 1</b>		<b>Group Type: sip</b>	
IMS Enabled? n		<b>Transport Method: tls</b>	
Q-SIP? n			
IP Video? n		Enforce SIPS URI for SRTP? y	
<b>Peer Detection Enabled? y</b>		<b>Peer Server: SM</b>	
 <b>Near-end Node Name: procr</b>		 <b>Far-end Node Name: SM63vmpg</b>	
<b>Near-end Listen Port: 5061</b>		<b>Far-end Listen Port: 5061</b>	
		<b>Far-end Network Region: 1</b>	
<b>Far-end Domain:</b>			
Incoming Dialog Loopbacks: eliminate		Bypass If IP Threshold Exceeded? n	
<b>DTMF over IP: rtp-payload</b>		RFC 3389 Comfort Noise? n	
Session Establishment Timer(min): 3		<b>Direct IP-IP Audio Connections? y</b>	
Enable Layer 3 Test? y		IP Audio Hairpinning? n	
H.323 Station Outgoing Direct Media? n		Initial IP-IP Direct Media? n	
		Alternate Route Timer(sec): 6	

Configure the **Trunk Group** form as shown below. This trunk group is used for calls to and from Communications Portal. Enter a descriptive name in the **Group Name** field. Set the **Group Type** field to **sip**. Enter a **TAC** code compatible with the Communication Manager dial plan. Set the **Service Type** field to **tie**. Specify the signaling group associated with this trunk group in the **Signaling Group** field, and specify the **Number of Members** supported by this SIP trunk group. Accept the default values for the remaining fields.

change trunk-group 1		Page 1 of 21	
TRUNK GROUP			
Group Number: 1	<b>Group Type: sip</b>	CDR Reports: y	
<b>Group Name: SIP TRK</b>	COR: 1	TN: 1	<b>TAC: *11</b>
Direction: two-way	Outgoing Display? y	Night Service:	
Dial Access? n			
Queue Length: 0			
<b>Service Type: tie</b>	Auth Code? n		
		Member Assignment Method: auto	
		Signaling Group: 1	
		Number of Members: 10	

On **Page 2** of the trunk-group form the **Preferred Minimum Session Refresh Interval (sec)** field should be set to a value mutually agreed with Presence to prevent unnecessary SIP messages during call setup. Session refresh is used throughout the duration of the call, to check the other side has not gone away, for the compliance test a value of **600** was used.

change trunk-group 1		Page 2 of 21	
Group Type: sip			
TRUNK PARAMETERS			
Unicode Name: auto			
Redirect On OPTIM Failure: 5000			
SCCAN? n	Digital Loss Group: 18		
<b>Preferred Minimum Session Refresh Interval(sec): 600</b>			
Disconnect Supervision - In? y Out? y			
XOIP Treatment: auto		Delay Call Setup When Accessed Via IGAR? N	

Settings on **Page 3** can be left as default.

change trunk-group 1	<b>Page 3 of 21</b>
TRUNK FEATURES	
ACA Assignment? n	Measured: none
	Maintenance Tests? y
Numbering Format: private	UI Treatment: service-provider
	Replace Restricted Numbers? n
	Replace Unavailable Numbers? n
Modify Tandem Calling Number: no	
Show ANSWERED BY on Display? y	

Settings on **Page 4** are as follows.

change trunk-group 1	<b>Page 4 of 21</b>
PROTOCOL VARIATIONS	
Mark Users as Phone? n	
Prepend '+' to Calling/Alerting/Diverting/Connected Number? n	
Send Transferring Party Information? y	
Network Call Redirection? n	
Send Diversion Header? n	
Support Request History? y	
Telephone Event Payload Type: 101	
Convert 180 to 183 for Early Media? n	
Always Use re-INVITE for Display Updates? n	
Identity for Calling Party Display: P-Asserted-Identity	
Block Sending Calling Party Location in INVITE? n	
Accept Redirect to Blank User Destination? y	
Enable Q-SIP? n	




## 6. Configure Avaya Aura® Session Manager

This section provides the procedures for configuring Session Manager. Session Manager is configured via System Manager. The procedures include the following areas:


- Log in to Avaya Aura® Session Manager
- Configure SIP Domain
- Configure Location
- Configure SIP Entities
- Configure Routing Policies
- Configure Dial Patterns

### 6.1. Log in to Avaya Aura® System Manager

Access the System Manager using a Web Browser by entering **http://<FQDN>/SMGR**, where **<FQDN>** is the fully qualified domain name of System Manager or **http://<IP Address>/SMGR**. Log in using appropriate credentials.




Once logged in click on **Routing** as highlighted.




## 6.2. Configure SIP Domain

Click on **Domains** in the left window. If there is not a domain already configured click on **New** highlighted below.




Enter the name of the domain note this was referenced in **Section 5.5**. The **Type** should be **sip**. Click on **Commit**, once done.



## 6.3. Configure Location

Select **Locations** from the left window and select **New** from the main window.



Enter a suitable name for the location and scroll down to the bottom of the page and enter the IP addresses associated with the location in the case there are two ranges **10.10.40.x** and **192.168.50.x** and click on **Add**. Once completed, click on **Commit** to continue.

**AVAYA**  
Aura® System Manager 6.3

Home / Elements / Routing / Locations

**Location Details** Commit Cancel

**General**

\* Name: DevConnectPG63

Notes:

**Dial Plan Transparency in Survivable Mode**

Enabled: ☐

Listed Directory Number:

Associated CM SIP Entity:

\* Minimum Multimedia Bandwidth: 64 Kbit/Sec

\* Default Audio Bandwidth: 80 Kbit/sec

**Alarm Threshold**

Overall Alarm Threshold: 80 %

Multimedia Alarm Threshold: 80 %

\* Latency before Overall Alarm Trigger: 5 Minutes

\* Latency before Multimedia Alarm Trigger: 5 Minutes

**Location Pattern**

Add Remove

2 Items


<input type="checkbox"/>	IP Address Pattern	Notes
<input type="checkbox"/>	* 10.10.40.*	
<input type="checkbox"/>	* 192.168.50.*	

Select : All, None

Commit Cancel


## 6.4. Configure Adaptation

To configure a new Adaptation select **Adaptations** from the left window and click on **New** from the main window.



Enter a suitable **Name** and select **DigitConversionAdapter** for the **Module Name**. Select **Name-Value Parameter** as the **Module Parameter Type**. Add the following Parameters:

- | Name   | Value    |
|--------|----------|
| fromto | true     |
| iodstd | “domain” |
| iosrcd | “domain” |



Continue to add the following Parameters:

- | Name    | Value                              |
|---------|------------------------------------|
| • odstd | “Communications Portal IP Address” |
| • osrcd | “Session Manager IP Address”       |

Click on **Commit** once completed.

AVAYA  
Aura® System Manager 6.3

Home / Elements / Routing / Adaptations

Adaptation Details **Commit** **Cancel**

General

\* Adaptation Name: EngHouse

Module Name: DigitConversionAdapter

Module Parameter Type: Name-Value Parameter

**Add** **Remove**

Name	Value
odstd	10.10.40.40
osrcd	10.10.40.34


Select : All, None Page 2 of 2

Egress URI Parameters:


Notes:

## 6.5. Configure SIP Entity for Enghouse Interactive Communications Portal

Select **SIP Entities** from the left window and click on **New** in the main window.




Enter a suitable **Name** and ensure that the **Adaptation** that was created in **Section 6.4** is used. Enter the **Location** that was configured in **Section 6.2** and the correct **Time Zone**.



## 6.6. Configure Entity Link for Enghouse Interactive Communications Portal

Select **Entity Link** from the left window and click on **New** in the main window.



AVAYA Aura System Manager 6.3

Home / Elements / Routing / Entity Links


Entity Links

New Edit Delete Duplicate More Actions

7 Items Filter: Enable

<input type="checkbox"/>	Name	SIP Entity 1	Protocol	Port	SIP Entity 2	DNS Override	Port	Connection Policy	Deny New Service	Notes
<input type="checkbox"/>	AAMessaging	SM63vmpg	TCP	5060	AAMessaging	<input type="checkbox"/>	5060	trusted	<input type="checkbox"/>	
<input type="checkbox"/>	ASCOMDECT1	SM63vmpg	TCP	5060	ASCOMDECT1	<input type="checkbox"/>	5060	trusted	<input type="checkbox"/>	
<input type="checkbox"/>	SM63vmpg_CM62_5061_TLS	SM63vmpg	TLS	5061	CM62	<input type="checkbox"/>	5061	trusted	<input type="checkbox"/>	
<input type="checkbox"/>	SM63vmpg_CM63VMGP_5060_TCP	SM63vmpg	TCP	5060	CM63VMGP	<input type="checkbox"/>	5060	trusted	<input type="checkbox"/>	

Select the correct **SIP Entity** that was created in **Section 6.5** and ensure that **TCP** is used as the **Protocol**. Note the **Port** is **5060**.



AVAYA Aura System Manager 6.3

Home / Elements / Routing / Entity Links

Entity Links

Commit Cancel


1 Item Filter: Enable

<input type="checkbox"/>	Name	SIP Entity 1	Protocol	Port	SIP Entity 2	DNS Override	Port	Connection Policy	Deny New Service	Notes
<input type="checkbox"/>	*SM63vmpg_Enghous	*SM63vmpg	TCP	*5060	*EnghouseCP	<input type="checkbox"/>	*5060	trusted	<input type="checkbox"/>	


Select : All, None

## 6.7. Configure Routing Policy for Enghouse Interactive Communications Portal

Select **Routing Policies** from the left window and click on **New** in the main window.



Enter a suitable **Name** and click on **Select** highlighted in order to associate this routing policy with a SIP Entity.





Select the **EnghouseCP** SIP Entity created in **Section 6.5** and click on **Commit** when done (not shown).

The screenshot shows the Avaya Aura System Manager 6.3 interface. The left sidebar contains a navigation menu with 'Routing Policies' highlighted. The main content area displays the 'SIP Entities' page. A table lists 11 items, with 'EnghouseCP' highlighted. The table has columns for Name, FQDN or IP Address, Type, and Notes.

Name	FQDN or IP Address	Type	Notes
AA Messaging	192.168.50.60	SIP Trunk	
AastraBS1	10.10.40.75	SIP Trunk	
AastraBS2	10.10.40.76	SIP Trunk	
ASCOMDECT1	10.10.40.181	SIP Trunk	
CM62	192.168.50.13	CM	
CM63VMGP	10.10.40.31	CM	
CS1KPG1	10.10.40.111	SIP Trunk	
CS1KPG2	192.168.50.99	SIP Trunk	
<b>EnghouseCP</b>	<b>10.10.40.40</b>	<b>SIP Trunk</b>	
IPOfficeR9	10.10.40.50	SIP Trunk	
SM63vmgp	10.10.40.34	Session Manager	

## 6.8. Configure Dial Pattern for Enghouse Interactive Communications Portal

In order to route calls to the Communications Portal a dial pattern is created pointing to the SIP Entity. Select **Dial Patterns** from the left window and click on **New** in the main window.

The screenshot shows the Avaya Aura System Manager 6.3 interface. The left sidebar contains a navigation menu with 'Dial Patterns' highlighted. The main content area displays the 'Dial Patterns' page. A table lists 6 items, with the 'New' button highlighted. The table has columns for Pattern, Min, Max, Emergency Call, Emergency Type, Emergency Priority, SIP Domain, and Notes.

Pattern	Min	Max	Emergency Call	Emergency Type	Emergency Priority	SIP Domain	Notes
10	4	4				devconnect.local	
2	4	4				devconnect.local	CM63
30	4	4				-ALL-	CS1KPG1
5999	4	5				-ALL-	AURA_Messaging
70	4	4				devconnect.local	CS1KPG1

Enter the number to be routed noting this will be the same number outlined in **Section 5.4**. Note the **SIP Domain** is that configured in **Section 6.2**. Click on **Add** to select the SIP Entity.

Home / Elements / Routing / Dial Patterns

**Dial Pattern Details** [Commit] [Cancel] [Help ?]

**General**

\* Pattern: 43  
 \* Min: 4  
 \* Max: 4

Emergency Call: ☐  
 Emergency Priority: 1  
 Emergency Type:   
 SIP Domain: devconnect.local  
 Notes: To Enghouse CP

**Originating Locations and Routing Policies**

[Add] [Remove]

1 Item

Originating Location Name	Originating Location Notes	Routing Policy Name	Rank	Routing Policy Disabled	Routing Policy Destination	Routing Policy Notes

Tick on the **Originating Location** as shown below and select the **Enghouse** Routing Policy. Click on **Select** once complete (not shown).

**Originating Location**

☐ Apply The Selected Routing Policies to All Originating Locations

1 Item

Name	Notes
<input checked="" type="checkbox"/> DevConnectPG63	

Select : All, None

**Routing Policies**

7 Items

Name	Disabled	Destination	Notes
<input type="checkbox"/> ToAAMessaging	<input type="checkbox"/>	AAMessaging	
<input type="checkbox"/> ToCM62	<input type="checkbox"/>	CM62	
<input type="checkbox"/> ToCM63VMPPG	<input type="checkbox"/>	CM63VMPPG	
<input type="checkbox"/> ToCS1KPG1	<input type="checkbox"/>	CS1KPG1	
<input type="checkbox"/> ToCS1KPG2	<input type="checkbox"/>	CS1KPG2	
<input checked="" type="checkbox"/> To Enghouse	<input type="checkbox"/>	EnghouseCP	
<input type="checkbox"/> To IPOR9	<input type="checkbox"/>	IPOfficeR9	

Select : All, None

With the new Routing Policy in place, click on **Commit** as shown below.

Routing / Home / Elements / Routing / Dial Patterns [Help ?](#)

**Dial Pattern Details** **Commit** **Cancel**

**General**

\* **Pattern:** 43

\* **Min:** 4

\* **Max:** 4

**Emergency Call:** ☐

**Emergency Priority:** 1

**Emergency Type:**

**SIP Domain:** devconnect.local

**Notes:** To Enghouse CP

**Originating Locations and Routing Policies**

**Add** **Remove**


1 Item [Filter: Enable](#)

<input type="checkbox"/>	Originating Location Name	Originating Location Notes	Routing Policy Name	Rank	Routing Policy Disabled	Routing Policy Destination	Routing Policy Notes
<input type="checkbox"/>	DevConnectPG63		To Enghouse	0	<input type="checkbox"/>	EnghouseCP	


Select : All, None

## 6.9. Configure Avaya Aura® Communication Manager SIP Entity

Select **SIP Entities** from the left window and click on **New** in the main window.



Enter a suitable **Name** and ensure the **Location** that was configured in **Section 6.2** and the correct **Time Zone** is entered.



## 6.10. Configure Avaya Aura® Communication Manager Entity Link

Select **Entity Link** from the left window and click on **New** in the main window.

Avaya Aura System Manager 6.3

Home / Elements / Routing / Entity Links

Entity Links

New Edit Delete Duplicate More Actions

7 Items Filter: Enable

<input type="checkbox"/>	Name	SIP Entity 1	Protocol	Port	SIP Entity 2	DNS Override	Port	Connection Policy	Deny New Service	Notes
<input type="checkbox"/>	AAMessaging	SM63vmppg	TCP	5060	AAMessaging	<input type="checkbox"/>	5060	trusted	<input type="checkbox"/>	
<input type="checkbox"/>	ASCOMDECT1	SM63vmppg	TCP	5060	ASCOMDECT1	<input type="checkbox"/>	5060	trusted	<input type="checkbox"/>	
<input type="checkbox"/>	SM63vmppg_CM62_5061_TLS	SM63vmppg	TLS	5061	CM62	<input type="checkbox"/>	5061	trusted	<input type="checkbox"/>	
<input type="checkbox"/>	SM63vmppg_CM63VMPPG_5060_TCP	SM63vmppg	TCP	5060	CM63VMPPG	<input type="checkbox"/>	5060	trusted	<input type="checkbox"/>	

Select the correct **Sip Entity** that was created in **Section 6.9** and ensure that **TCP** is used as the **Protocol**. Note the **Port** is **5060**.

Avaya Aura System Manager 6.3

Home / Elements / Routing / Entity Links

Entity Links

Commit Cancel

1 Item Filter: Enable


<input type="checkbox"/>	Name	SIP Entity 1	Protocol	Port	SIP Entity 2	DNS Override	Port	Connection Policy	Deny New Service	Notes
<input type="checkbox"/>	*SM63vmppg_CM63VM	*SM63vmppg	TCP	*5060	*CM63VMPPG	<input type="checkbox"/>	*5060	trusted	<input type="checkbox"/>	

Select : All, None


Commit Cancel

## 6.11. Configure Avaya Aura® Communication Manager Routing Policy

Select **Routing Policies** from the left window and click on **New** in the main window.



Enter a suitable **Name** and click on **Select** highlighted in order to associate this routing policy with a SIP Entity. Select the **Communication Manager** SIP Entity created in **Section 6.9** (not shown) and click on **Commit** when done.



Select the Communication Manager SIP Entity as shown below and click on **Select**.

AVAYA  
Aura® System Manager 6.3

Home / Elements / Routing / Routing Policies

SIP Entities

Select Cancel

SIP Entities

11 Items Filter: Enable

Name	FQDN or IP Address	Type	Notes
◉ AAMessaging	192.168.50.60	SIP Trunk	
◉ AastraBS1	10.10.40.75	SIP Trunk	
◉ AastraBS2	10.10.40.76	SIP Trunk	
◉ ASCOMDECT1	10.10.40.181	SIP Trunk	
◉ CM62	192.168.50.13	CM	
◉ CM63VMPG	10.10.40.31	CM	
◉ CS1KPG1	10.10.40.111	SIP Trunk	
◉ CS1KPG2	192.168.50.99	SIP Trunk	
◉ EnghouseCP	10.10.40.40	SIP Trunk	
◉ IPOfficeR9	10.10.40.50	SIP Trunk	
◉ SM63vmpg	10.10.40.34	Session Manager	

Select : None

Once this is select the original screen is shown with the selected SIP Entity in place as highlighted below. Click on **Commit** once this is shown.

AVAYA  
Aura® System Manager 6.3

Home / Elements / Routing / Routing Policies

Routing Policy Details

Commit Cancel

General

\* Name: ToCM63VMPG

Disabled: ☐

\* Retries: 0

Notes:

SIP Entity as Destination

Select

Name	FQDN or IP Address	Type	Notes
CM63VMPG	10.10.40.31	CM	

## 6.12. Configure Avaya Aura® Communication Manager Dial Pattern

In order to route calls to Communication Manager a dial pattern is created pointing to the SIP Entity. Select **Dial Patterns** from the left window and click on **New** in the main window.

The screenshot shows the Avaya Aura System Manager 6.3 interface. The left sidebar contains a navigation menu with 'Dial Patterns' highlighted. The main window displays the 'Dial Patterns' list with the following data:

Pattern	Min	Max	Emergency Call	Emergency Type	Emergency Priority	SIP Domain	Notes
10	4	4	<input type="checkbox"/>			devconnect.local	
2	4	4	<input type="checkbox"/>			devconnect.local	CM63
30	4	4	<input type="checkbox"/>			-ALL-	CS1KPG1
5999	4	5	<input type="checkbox"/>			-ALL-	AURA_Messaging
70	4	4	<input type="checkbox"/>			devconnect.local	CS1KPG1

Buttons at the top: New, Edit, Delete, Duplicate, More Actions. Filter: 6 Items.

Enter the number to be routed noting this will be extension numbers of the Communication Manager deskphones, in this case **2xxx**. Note the **SIP Domain** is that configured in **Section 6.2**. Click on **Add** to select the SIP Entity.

The screenshot shows the 'Dial Pattern Details' form in the Avaya Aura System Manager 6.3 interface. The form is titled 'Dial Pattern Details' and includes the following fields:

- Pattern:** 2
- Min:** 4
- Max:** 4
- Emergency Call:** ☐
- Emergency Priority:** 1
- Emergency Type:**
- SIP Domain:** devconnect.local
- Notes:** To CM63

Buttons: Commit, Cancel, Help ?

**Originating Locations and Routing Policies**

Buttons: Add, Remove

1 Item

Originating Location Name	Originating Location Notes	Routing Policy Name	Rank	Routing Policy Disabled	Routing Policy Destination	Routing Policy Notes
---------------------------	----------------------------	---------------------	------	-------------------------	----------------------------	----------------------



Tick on the **Originating Location** as shown below and select the **Communication Manager** Routing Policy. Click on **Select** once complete.

**Dial Patterns**

1 Item	Name	Notes
<input checked="" type="checkbox"/>	DevConnectPG63	

Select : All, None

**Routing Policies**

7 Items	Name	Disabled	Destination	Notes
<input type="checkbox"/>	ToAAMessaging	<input type="checkbox"/>	AAMessaging	
<input type="checkbox"/>	ToCM62	<input type="checkbox"/>	CM62	
<input checked="" type="checkbox"/>	ToCM63VMPG	<input type="checkbox"/>	CM63VMPG	
<input type="checkbox"/>	ToCS1KPG1	<input type="checkbox"/>	CS1KPG1	
<input type="checkbox"/>	ToCS1KPG2	<input type="checkbox"/>	CS1KPG2	
<input type="checkbox"/>	To Enghouse	<input type="checkbox"/>	EnghouseCP	
<input type="checkbox"/>	To IPOR9	<input type="checkbox"/>	IPOfficeR9	

Select : All, None

Select Cancel

When **Select** above is clicked, the original screen will appear showing this selected Routing Policy as is highlighted below. Once this is shown correctly, click on **Commit** to finish.

**Dial Pattern Details**

Commit Cancel

**General**

\* Pattern: 2

\* Min: 4

\* Max: 4

Emergency Call: ☐

Emergency Priority: 1

Emergency Type:

SIP Domain: devconnect.local

Notes: To CM63

**Originating Locations and Routing Policies**


Add Remove

1 Item	Originating Location Name	Originating Location Notes	Routing Policy Name	Rank	Routing Policy Disabled	Routing Policy Destination	Routing Policy Notes
<input checked="" type="checkbox"/>	DevConnectPG63		ToCM63VMPG	0	<input type="checkbox"/>	CM63VMPG	


Select : All, None

## 7. Configuration of Enghouse Interactive Communications Portal 9.0


The Telephony module of Communications Portal which provides the connection to Session Manager is provided by a Dialogic Boards Driver. This driver completely caters for the telephony module of this solution. To configure the Dialogic Boards Driver open the **CP Console 9.0** by double clicking on the shortcut as shown below.




In the left window, navigate to **Servers** → [Server Name] → **Engine Settings** → **Drivers** → **Dialogic boards Driver**.




In the main window scroll down to **HMP Startup Options**, ensure that **Auto SIP OPTIONS** is set to **Yes**. **SIP Transport Protocol** is set to **User Defined** and **TCP** is **enabled**, also note the **Default Transport** is set to **TCP**.




Click on **Boards** in the left window and select the **HMP (IP)** board in the main window.



The following window is then displayed; ensure that **Enable re-INVITE feature** is set to **Yes**.



Scroll down to **Codec 1, 2, 3...** and select the proper codec to be used. In the example below **G.711 A-Law** and **G.711 u-Law** are selected.




Please note that configuration of Communications Portal with regards to the setup of the IVR is outside the scope of these Application Notes, for more information on this setup please refer to **Section 10** of these Application Notes.

## 8. Verification Steps


To verify a successful configuration of Enghouse Interactive Communications Portal and Session Manager a call is placed from a Communication Manager telephone to the Communications Portal with the caller getting answered successfully hearing clear and audible speech.

### 8.1. Verify Enghouse Interactive Communications Portal SIP Entity is up

Log in to System Manager as per **Section 6.1**. From the main menu select Session Manager as shown below.



Navigate to **System Status** → **SIP Entity Monitoring**.



Select the **EnghouseCP** SIP Entity.

Configuration	Session Manager	Type	Monitored Entities					
			Down	Partially Up	Up	Not Monitored	Deny	Total
System Status	<input type="checkbox"/>							
<b>SIP Entity Monitoring</b>	<input type="checkbox"/>	Core	3	0	7	0	0	10
Managed Bandwidth Usage								
Security Module Status								
SIP Firewall Status								
Registration Summary								
User Registrations								
Session Counts								
System Tools								
Performance								

Select: All, None

All Monitored SIP Entities

Run Monitor

10 Items | Refresh Filter: Enable


SIP Entity Name
<input type="checkbox"/> CM62
<input type="checkbox"/> AastraBS1
<input type="checkbox"/> AastraBS2
<input type="checkbox"/> AAMessaging
<input type="checkbox"/> ASCOMDECT1
<input type="checkbox"/> IPOfficeR9
<input type="checkbox"/> <b>EnghouseCP</b>
<input type="checkbox"/> CS1KPG2

Note that both the **Conn. Status** and **Link Status** show **UP**.


Application Configuration	1 Items   Refresh Filter: Enable							
	Session Manager Name	SIP Entity Resolved IP	Port	Proto.	Deny	Conn. Status	Reason Code	Link Status
System Status	<input type="radio"/>							
<b>SIP Entity Monitoring</b>	<b>SM63vmpg</b>	10.10.40.40	5060	TCP	FALSE	UP	200 OK	UP
Managed Bandwidth Usage								
Security Module Status								
SIP Firewall Status								
Registration Summary								
User Registrations								
Session Counts								
System Tools								
Performance								

## 8.2. Verify Enghouse Interactive Communications Portal IVR script

Open the **CP Console 9.0** by double clicking on the shortcut as shown below.



Channel 1 below has the script **Envox Central** associated with it, this should also show as green.





## 9. Conclusion

These Application Notes describe the configuration steps required for Enghouse Interactive Communications Portal 9.0 to successfully interoperate with Avaya Aura® Session Manager R6.3 and Avaya Aura® Communication Manager R6.3. All feature functionality and serviceability test cases were completed successfully as outlined in **Section 2.2**.

## 10. Additional References

This section references the Avaya and Enghouse product documentation that are relevant to these Application Notes.

Product documentation for Avaya products may be found at <http://support.avaya.com>.

- [1] *Administering Avaya Aura® Communication Manager*, Document ID 03-300509
- [2] *Avaya Aura® Communication Manager Feature Description and Implementation*, Document ID 555-245-205
- [3] *Administering Avaya Aura® Session Manager*, Release 6.3, 03-603324

Product documentation for Enghouse Interactive Communications Portal can be obtained by visiting the following website, [www.enghouseinteractive.com](http://www.enghouseinteractive.com)

---

**©2014 Avaya Inc. All Rights Reserved.**

Avaya and the Avaya Logo are trademarks of Avaya Inc. All trademarks identified by ® and ™ are registered trademarks or trademarks, respectively, of Avaya Inc. All other trademarks are the property of their respective owners. The information provided in these Application Notes is subject to change without notice. The configurations, technical data, and recommendations provided in these Application Notes are believed to be accurate and dependable, but are presented without express or implied warranty. Users are responsible for their application of any products specified in these Application Notes.

Please e-mail any questions or comments pertaining to these Application Notes along with the full title name and filename, located in the lower right corner, directly to the Avaya DevConnect Program at [devconnect@avaya.com](mailto:devconnect@avaya.com).